



325 Industry Drive
Carlisle, Ohio 45005
(937)-746-9750
1-800-977-6872

Industrial Electronic Service

March 1, 2006

DC-40T, Count down timer

- 1) This timer requires 120Volt AC for operation.
- 2) When the timer is first connected to power, it will set itself to zero (00:00).
- 3) The wired remote (RM-25) functions are as follows:
Toggle switch is used to select which mode the user wants the display to be in, RUN or SET. The RUN mode will display the time HHMM or MMSS or SSTH and the SET mode will display the set time to be count down from in hours and minutes.
Red push button, in RUN mode, is used for start stop. In the SET mode it is used for setting the hours (this can only be done when stopped).
Black push button, in RUN mode, is used for RESET TO THE LAST VALUE.(this can only be done when stopped). In the SET mode it is used for setting the minutes (this can only be done when stopped).
Both red and black: In the SET mode, will reset the count down time to zero 00:00.
NOTE: SET mode will not function if timer is running.
- 4) This timer will flash for tens seconds after reaching 00:00.
- 5) Simply push the RESET TO LAST VALUE button and it is ready for another count down.

Thank you for purchasing this DC-Digital timer.

We Give you the Time!

